

Function/Arbitrary Waveform Generator



Model	33210A
Producer	Agilent Technologies
Installation	2013
Location	EAT 74

Information

The function/arbitrary waveform generator is able to provide output of sine, square, triangle, ramp, pulse and others.

Specification

- 10 MHz Sine and Square waveforms
- Pulse, Ramp, Triangle, Noise, and DC waveforms
- Optional 14-bit, 50 MSa/s, 8K point Arbitrary Waveform Generator
- AM, FM, and PWM modulation types
- Linear & logarithmic sweeps and burst operation
- 10 mVpp to 10 Vpp amplitude range
- Graph mode for visual verification of signal settings